



CONNECTION		VALUE	NOTES:
SPECIFICATION			
RATED VOLTAGE(V):		110	1.THE LEAD WIRE OF BIG MOTOR CAN NOT BE PULLED FORCIBLY TO AVOID INTERNAL POOR CONDUCTIVITY.
NO LOAD CURRENT(mA):		≤700	2.PREVENT GEAR MOTOR FROM BEING SHOCKED OR DROPPING IN MOUNTING PROCESS.IT IS PROHIBITED TO STRIKE AND CRUSH DIRECTLY ON REDUCER OUTPUT SHAFT.
NO LOAD SPEED(RPM):		8.6±0.8	3.IT IS NECESSARY TO BE CAREFUL THAT THE ADHESIVE DOES NOT SPREAD ALONG THE SHAFT AND FLOW INTO THE BEARING.
RATED LOAD TORQUE(kgf.cm):		50	4.DO NOT TURN A GEARED MOTOR BY ITS OUTPUT SHAFT WHEN,FOR EXAMPLE,ARRANGING ITS POSITION SO AS TO INSTALL IT.
RATED CURRENT(mA):		≤800	5.USE WITH A LOAD THAT EXCEEDS THE RATED TORQUE WILL BE REDUCE THE LIFETIME OF GEAR MOTOR.
RATED LOAD SPEED(RPM):		7.8±0.7	6.CHECK MOTOR RUNNING WHEN IT IS POWER ON BEFORE INSTALLATION AND MAKE SURE PERFORMANCE MEET REQUEST .
STALL CURRENT(mA):		—	
STALL TORQUE(kgf.cm):		—	
ROTATION DIRECTION		CW/CCW	
		APVD	9.29.2022
		CHKD	
1:1		DRN	
SCALE	SIGNATURE	DATE	
			<b>DC GEARBOX MOTOR</b>
			<b>FGB-6126-110V-G392</b>