



SPECIFICATION	CONNECTION	VALUE	NOTES:
RATED VOLTAGE(V);		110	1.THE LEAD WIRE OF BIG MOTOR CAN NOT BE PULLED FORCIBLY TO AVOID INTERNAL POOR CONDUCTIVITY.
NO LOAD CURRENT(mA);		≤500	2.PREVENT GEAR MOTOR FROM BEING SHOCKED OR DROPPING IN MOUNTING PROCESS.IT IS PROHIBITED TO STRIKE AND CRUSH DIRECTLY ON REDUCER OUTPUT SHAFT.
NO LOAD SPEED(RPM);		10±1	3.IT IS NECESSARY TO BE CAREFUL THAT THE ADHESIVE DOES NOT SPREAD ALONG THE SHAFT AND FLOW INTO THE BEARING.
RATED LOAD TORQUE(kgf.cm);		40	4.DO NOT TURN A GEARED MOTOR BY ITS OUTPUT SHAFT WHEN, FOR EXAMPLE, ARRANGING ITS POSITION SO AS TO INSTALL IT.
RATED CURRENT(mA);		≤550	5.USE WITH A LOAD THAT EXCEEDS THE RATED TORQUE WILL BE REDUCE THE LIFETIME OF GEAR MOTOR.
RATED LOAD SPEED(RPM);		8±0.8	6.CHECK MOTOR RUNNING WHEN IT IS POWER ON BEFORE INSTALLATION AND MAKE SURE PERFORMANCE MEET REQUEST .
STALL CURRENT(mA);		—	
STALL TORQUE(kgf.cm);		—	
ROTATION DIRECTION		CW/CCW	
			APVD
			CHKD
			DRN
			9.29.2022
			1:1
			SCALE
			SIGNATURE
			DATE
			DC GEARBOX MOTOR
			FGF-6130-110V-G277